


H-Power Connect

THE ONLY CABINET ABLE TO MANAGE THE PUMP AND LIGHTING BY BLUETOOTH

- **2 timers for filtering and 1 timer for the lighting**
- **Automatic calibration** of the outlet for the filter pump
- **Integrated protection against overloads**
- **Several models to choose from, depending on customer requirements:** 50, 100 and 300 W transformers



Download the "HPOWER" application to be able to control remotely your pool with your smartphone



Remote Control

	Description
Supply	230V~ -50/60Hz
Pump outlet	14A, single-phase models
Lighting outlet (depends on model)	230V~/5A • 12V /50W (T50 W) • 12V~/100W (T100W) • 12V~/300W (T300W)
Indicators	Pump in operation, Alarm, Filter programmes, Auxiliary output and Time
Protections	Motor overload
Overload protection	20% higher than nominal current
4-Digit LED display	Time, Settings and Alarms
Auxiliary relay	Dry contact 250V / 5A maximum
Maximum cable cross-sections	4 mm ² (power) / 2.5 mm ² (control)
IP rating / Temperature	IP65/-10°...+55°C
Informations	Bluetooth interface (-B) • Radio remote control • External probe for atmospheric temperature

	Item	Description
SINGLE PHASE	HPOW230B	Electrical box H-POWER single phase + Bluetooth
	HPOW230BD	Electrical box H-POWER single phase with differential + Bluetooth
	HPOW230BDT50	Electrical box H-POWER single phase with differential and transformer 50W + Bluetooth
	HPOW230BDT100	Electrical box H-POWER single phase with differential and transformer 100W + Bluetooth
	HPOW230BDT300	Electrical box H-POWER single phase with differential and transformer 300W + Bluetooth
THREE PHASE	HPOW400B	Electrical box H-POWER three phase + Bluetooth
	HPOW400BD	Electrical box H-POWER three phase with differential + Bluetooth
	HPOW400BDT50	Electrical box H-POWER three phase with differential and transformer 50W + Bluetooth
	HPOW400BDT100	Electrical box H-POWER three phase with differential and transformer 100W + Bluetooth